

CATV Power Supply (Super)

10Amps with 2 O/P Ports

6Amps with 1 O/P Port



Features:

- Built-In Power Insertors
- Suitable for CATV Networks
- Freq. 5 ~ 860 MHz
- Automatic Short Circuit Cut-Off
- Short Circuit Alarm Indicator
- Continuous Current Indication
- Output Voltage : 60VAC, 50Hz
- Output Ports for Easy Distribution
- Automatic Power Restoring Circuit - after removing short circuit

**Economical
in Price**



An International Quality Product from **ANALOG SYSTEMS**

website: www.sharpvisiononline.in

Email: sales@sharpvisiononline.in / analogsystems@vsnl.net

Comparison of Deluxe & Super Power Supplies



Deluxe	Super
1. Price Higher than Super Models	1. Economical
2. Power Insertors are free with Power Supplies. (2pcs with 6Amp Power Supply and 4pcs with 10Amp Power Supply)	2. All Power Insertors are built inside the Power Supply
3. Useful for long trunk cable. As even a small hum can amplify and distribute to all TV sets due to many amplifiers in series	3. Useful for short branch cables and economy is more important
4. High Linear Frequency Response of ± 0.5 dB from 5 to 860MHz	4. Frequency Response Linearity is ± 1.5 dB from 5 to 860MHz
5. More useful when no. of channels exceed 60 nos.	5. Useful for small systems

Power Supply 60V 6Amp with Amplifier Installation Diagram (Tentative)

